
European Command and Control Console System







HEADOLIARTERS

U.S. ARMY STRATEGIC COMMUNICATIONS COMMAND

WASHINGTON D.C. 20315

SUBJECT: European Command & Control Console System

SEE DISTRIBUTION TO:


- 1. It is my extreme pleasure to present the United States Army Strategic Communications Command publication - "European Command & Control Console System." The equipment system described in this brochure has been designed as a major portion of the technical support required for the European Command and Control System. The purpose of this brochure is to present the capabilities of this sophisticated communications control system and to elicit specific constructive comment.
- 2. Although the basic design is now "frozen" and the equipment in production, several retrofit modifications are planned. Whenever the functional system requirements dictate additional modifications, we are prepared to implement these changes on a similar basis; however, this equipment system will generate the need for functional system design reevaluation and in this context care should be exercised in proposing design changes both functional and technical.
- 3. In this solid state automated system the communicator himself is not a "middle man" in the technical support of the Command and Control System. Rather, precise control of the system element is directly available to "war room" personnel. In turn this will place the strategic and tactical commanders' operations staffs in a better position to develop and fully exploit the system capabilities.
- 4. Accordingly, I anticipate that a sophisticated system of this nature cannot be static, but must be dynamic in terms of the future. That future must be defined.

Commanding

DISTRIBUTION: Special

www.usarmygermany.com Capability to rapidly interconnect all users

- for command direction.
- · Continuously updates system status display at all control center locations.
- · Operational flexibility allows pushbutton transfer of system command and control to any of the headquarters' sites on a disciplined basis.
- · Permits rapid and direct connections to all users without the use of numerous hot lines-system uses only five trunks.
- · Preset conferences are effected by single
 - address operation
- · System survivability is assured through optimum design of network configura-
- tion No-talk-back operational mode for broadcast requirements.



NORTHERN

W GERMANY


EUROPEAN THEATER CONFERENCING NETWORK

Military operations in the European Theater require rapid, direct and reliable voice communications between head-quarters' locations and associated defense installations. In periods of energency, the control centers and field installations must be quickly interconnected for priority addresses. The Console System permits a designated control center to rapidly establish circuits to any or all users of this European Theater conferencing network.

Until a few years ago, such a conference system could be assembled only on a manual basis. At the distant stations of the various circuits, switchboard operators would be required to perform cord-switching operations for each conferee to connect control centers and tributary locations. However, the increasing speed of military operations requires more rapid and direct communication links than such facilities can provide. Now, through the use of digital control circuits, the Console System can directly establish theater-wide master conferences and present status data that indicates the disposition of all connected parties. Not only does the Console System permit all users to be immediately interconnected, but also provides a selection of preset conference arrangements that interconnect programmed conferees, Random conferencing capabilities allow local operators to establish unprogrammed conferences and to modify the composition of preset conferences on a demand basis. All conferences may be established for either talk-back or no-talk-back modes of operation.

Five dedicated mainline trunks of the ET-A and 486L long-haut communication networks constitute the backbone transmission links of the Console System. Broadband multichannel microwave equipment is utilized in the transmission links. The concept of the Console System is unique to a long-haid communication bring and communications via transmission links.

The Console System permits all conclerencing netcenters to perseat the conferencing network independently. However, a designnated control center maintains command of the system and may size any or all comferencing circuits for emergency use. This pre-emptive type of switching allows an over-all reduction in the number of hot lines necessary to operate this theater-wide conferencing network.



Operations Center

SYSTEM DELINEATION

Back control center of the Console System consists of an Operations Center and a Local Equipment Van. The Operations Center equipment is installed in a permanent building at primary headquarters in a van at dumark locations. The system is equipped for the control of up to 240 ribitary attains as well as a nominal number of telephones in each local area, and is expandable to 999 subscribers.

The system arrangement allows the grouping of tributeries to provide the most effective command communications commensurate with the quantity and complexity of equipment. Each tributary group is assigned to a nodal point station referred to as a Remote Equipment Van. Up to 24 tributaries can be accommodated by a Retributaries ca

www.usarmygermany.com



mote Equipment Van. All Local Equipment and Remote Equipment sites are bridged across five dedicated trunks that carry all Console System mainline communications. The console mainline equipments are permanently bridged to allow conference access without switching or otherwise interrupting mainline traffic. The tributaries are serviced as spurs from the Console Remote Equipment sites.

The mainline trunks are utilized as dedicated interstation channels interconnecting the Console System. At any time the channels may be individually assigned to any system function. At the console local equipment sites, the terminating circuitry is the operator and local drop telephone equipment, while at the console remote sites it consists of spuries to tributary sites.



Local Equipment Van

www.usarmygermany.com


THE OPERATIONAL CONCEPT


The Console System will establish up to four simultaneous telephone conferences, each of which may include any number of conferees. These conferences are established by means of the operator's consolette. Identical units are utilized at each Onerations Center.

The consolette is used by the operator to enter instructions into the system so that the necessary connections can be established between stations. The status wall display provides a listing of all the network stations and displays the incoming requests and status information associated with each sear. A cluster of visual indicators is associated with station entiry and supervisory functions such as those associated with techniques of the station entiry and supervisory functions such as those associated with telephone circuits. Additionally, each busy station is identified with one of the four trunk circuits by means of colored lamps.

The Console System provides automatic communications capabilities between system users under the supervision of designated command and control headquarters. Operations Centers of graded seniority participate in operation of the system. Through control consolettes, operators have rapid and continuous communications access to local drop circuits and tributary sites

The system is under command of a single Operations Center which has priority use of the system supervisory command channel. The remaining console local equipments will be in a NON COMMAND mode of operation. To provide organizational flexibility or during emergency circumstances, command of the system can be transferred to any one of the other Operations Centers. Whenever the system control is idle (floating), one of the STANDBY operators can obtain control of the system. The supervisory trunk can then be used by that operator to set up the desired communications. Upon completion the operator releases the supervisory command channel and allows control to be taken by one of the other console locations. However, in accordance with the command concept, the IN COMMAND operator can pre-empt control of the system by simply pressing the consolette





Conference Circuit Connections

CONFERENCING

Conferencing may be accomplished either on a pre-programmed basis or by building up a conference—adding tributaries, consoles, and local drops as required.

A master conference, the highest priority lime by the decade and any become teed a highest priority lime by the decade and lime by conference and lime by the lime

A preset conference call may be connected to a ready circuit or added to a busy circuit. An addressed preset conference consists of tributaries and consoles which are programmed on a conference patch panel. A maximum of seventeen preset conferences and one master conference can be programmed. Again, local drops must be addressed and connected to the conference by

their respective console operators. The number of addresses connected to a preset conference may be modified for a particular connection by the IN CONTROL operator; individual subscribers may be added to or disconnected from a preset conference.

A built-up conference is established by adding tributaries, consoles, and local drops to a conference circuit, as requested. Each subscriber must be individually addressed and connected.

System operation accommodates two modes of conferencing. One is the arrange-ment where every member of the pictoria, can talk to or receive from all ofter, members (TALK BACK); the other is with conferes connected by their receive paths permitting only the calling party to trans-time (NO TALK BACK). It was not not confered any conference the mode may be switched any conference the mode may be switched by the property of the calling party to trans-time to the conference of the



STATUS REPORTING

Continually undated status information is received at the console local sites from all system stations via the supervisory status channels. The data is decoded in local equipment logic circuitry and simultaneously compiled at all Operations Centers on wall displays. The status data contains all information descriptive of identity and state for the system's terminations and users. Since lamp indicators provide the interface between the system state and operator, it is important that information he displayed in a manner which is consistent with the anticipated type of operator response. To accomplish this, all conditions requiring immediate operator action are displayed in transient sequences (flashing slow or fast), while states which

WALL DISPLAY STATUS FORMAT							
Color	Temporal Pattern	Definition					
White	Steady on	Station idle, may be reached					
White	Fast flashing	Station is being called by operato has not yet responded					
Green	Steady on	Busy					
Green	Fast flashing	Request for operator service, or p call if one of circuit indicators of wall display is also lit					
Green	Slow flashing	Station is receiving "standby"					

operator

Lamp failure

Priority request for service

Out of service, acknowledged

New failure, not acknowledged b

can exist for indeterminate periods without requiring action are displayed in-q steady condition. An individual walf display panel is provided for each tributary, each local drop served, each preset conference, and each console local. All information pertaining to a particular user or conference is displayed on a single panel

using the listed wall display status format,

Fast flashing

Fast flashing

Steady on

Red

Red

Unlighted

COMMAND AND CONTROL SWITCHING

Command and control instructions are communicated between local, remote, and tributary sites using a number of carrier telegraph tone channels within the voice band. These channels may occupy the entire voice band, as in the case of the supervisory and ready circuits, or they may be used singly on a speech-plus-duplex basis. All supervisory and ready command sigmand the supervisory and ready command siglated that the supervisory and ready command supervisory and ready command sigture of the consoled that the supervisory of the consoled focal sites have identical command and control equipment.

The supervisory channel issues and receives commands to and from all sites to establish talking paths, to update the system status displays, and to verify the quality of the supervisory trunk,

The ready channel issues commands to all mainline sites to select a new circuit, to identify the circuit it is on, to establish the system's next talking path, to update its own status, and to verify the quality of the ready trunk transmission and reception

Command of the system is maintained by one console site only, but the command frequency transmitter of this site may be accessed by any one of the standardy console local sites. The console in control can only be pre-empted by the command operator; to therwise an operator must relinquish command may be transferred between command may be transferred between console local equipments on a pre-arranged schedule or to accommodate emergency situations.



System control of console local and remote equipment operation is accomplished by the supervisory and ready data circuits. The supervisory teletype circuit is a 24channel FSK multiplexed system, each channel canability being 60 wnm (45 haud). One of the TTY channels is assigned the supervisory command function. Other TTY channels in the group are assigned, one to each node and console, for the nurpose of reporting status and supervisory information. The supervisory data may be transmitted on any one of the five system mainlines: the other four would be utilized as conference circuits. The supervisory channel controls select matrix connections. tributary signaling messages, and trunk

matrix disconnects

ference channel is ready to be used in setting up the next system talking nath. If the system line designated as the Conference A channel is ready, the IN COMMAND console site is transmitting an FSK tone on that system line to all console sites; all console sites are returning a tone over the same line to the IN COMMAND console site; consequently, an operational transmit and receive nath is available. The ready channel controls trunk matrix connections and in addition, parallels supervisory channel operation when an emergency master conference is initiated Initial connection of supervisory and ready command transmitters to system lines is detected by the per-line supervisory and ready channel detectors. This information is then fed to the trunk matrix control which acts to connect the proper receive

The ready channel designates which con data circuits to their respective lines. STANDE STANDET CONSOL F CONSOL F CONSOLE CONSOLE COMMAND CONSOLE STATUS DATA FROM OTHER MAINLINE STATIONS SUPERVISORY CIRCUIT TTY CHANNELS STANDS CONSOL LOCAL REMOTE STATUS DATA FROM OTHER MAINLINE STATIONS READY CIRCUIT TTY CHANNELS

SUPERVISORY SIGNALING

Control of system operation is asserted by means of the supervisory command on message, which is generated by the console local equipment that is IN CONTROL.
It is by means of this message that all all instructions and orders pertaining to system operation are issued, and established all connections are established connections are broken down. The generation of the supervisory command message us is governed by the controls of the operator consolette.

The instructions for system operation originating with the IN CONTROL operator are introduced into the system through the use of the consolette pushbuttons. Operation of the pushbuttons causes the information to be inserted into storage circuits in the console local equipment. The lighting of indicator lamps on the consolette confirms that the information is contained in the storage circuits. The storage feature allows the operator to inspect the makeup of a message before placing it on the line. This permits a set-check-send routine by the operator in which he sets instructions, checks equipment response. and finally transmits the supervisory information

The retention of the supervisory command message in storage remains under the control of the operator. Not until he presses the EXECUTE pushbutton will the supervisory command message be transferred to the line from storage. The message is released serially from storage to the consumer to the supervisory command guints growering or the supervisory command against growering erroneous messages, the individual characters that constitute the outgoing message are checked for parity before transmission. Any error will suspend the generation of the supervisory command message and will cause a fault signal to be produced.

Throughout the Console System, status

and command information must be exchanged between the component equipments of which the system is comprised. This information in the form of digital characters is converted into audio frequency-shifted signals in a standard teletype (TTY) code and processed to modulate an rf carrier. Upon reception of the transmitted signals, the TTY information is extracted from the rf carrier and reconverted into digital characters. Data to he exchanged is first encoded into eightdigit characters consisting of six data bits, and start and stop hits for inter-equipment message synchronization. In order to eliminate any errors introduced during transmission, the three-out-of-six code used is checked for parity before being accepted by the receiving equipment. To increase the capacity so that the required exchange of information can be accommodated, the transmitted characters are arranged in a time-division sequence message frame, With such an arrangement, the significance attached to a character depends not only on the data bit coding, but also on the position occupied by the character in the message.

The Console System makes use of a variety of frame, or message formats. A 44-character format is used to provide control and status information from remote equipment to tributary equipment and to report status of tributaries to the local equipment. Status information from each tributary serviced by a single remote equipment uses a discrete message format directly related to the 44-character format received from the remote equipment. At the local equipment, information is assembled into one of three message formats depending on the information being encoded. In addition, the system uses a ready circuit acknowledge signal to denote the condition of the ready signal. Unlike other messages, this signal does not use digitally encoded characters. but rather employs one of the two FSK tones to transfer information.

SYSTEM

LOCAL EQUIPMENT

The console local equipment establishes the nerve center for system operations. Essentially, it consists of a control Operations centrally and the constraint of the control of the contro

CAPARII ITIES

- Issue commands to the system to establish, modify, and terminate calls.
- Accept commands from the system and act on them to the extent that they pertain to the site at which the van is located.
- Accept and process status information from all sites.
- from all sites.

 Display status of all system sites on the
- status display for use by the operators.

 Accept input commands from operators via the consolettes.

- Provide means for moving system com-
- mand between the console local sites.

 When in command, provide means for delegating system operational control to various console local sites.
- When in command, provide means for maintaining system connectivity to the
- maximum extent possible.


 When in command, maintain the supervisory circuits necessary to perform
- visory circuits necessary to perform command and status functions.

 • When in command, maintain the ready
- circuit.

 When in command, issue status information regarding all existent conferences in the system.
- Provide means for recording system
- conferences.

 Provide means for calling the local drops either locally or on a system conference.
- Acommodate the assignment of digital addresses to subscribers in a random manner and display related status information in numerical order on the status display.
- Accommodate the assignment of tributaries to the preset conferences.
- · Record on tape voice communications.
- Issue status to all other console sites.
 Display fault summary indications.
- Program preset conference and address







REMOTE EQUIPMENT

The console remote equipment provides automatic connection of main line conference trunks to tributary equipment spur circuits under control of the supervisory and ready channels. The remote equipment is configured for unattended operation and completely contained in a single mobile and a completely contained in a single mobile and a console the control of the con

The five main line trunks are bridged to the remote equipment circuits. The supervisory channel transmits the command data message from the IN COMMAND console local to remote equipment digital data and switching equipment. This circuitry decodes the message and routes the resultant action, conference, and address selection signals to matrix and tributary control circuits. Accordingly, one of the four conference channels is connected to the appropriate tributary spur circuit and command data is converted to the remotetor-tributary message format.

Each addressed tributary then trujentils, aback to the remote outpinned, on assparate return link, a message comprised of digital data and audio portions. The remote, TTY modern equipment separates the signal and audio portion. The addio portion is connected to the designated conference, and the digital data (tributary status characteristics) and the digital data (tributary status characteristics) and applied to the supervisory status characteristics.

TRIBUTARY EQUIPMENT

The tributary equipment provides the facilities to allow the subscriber at a tributary site to have access to the Console System communications network. Tributary equipment is linked to the network through nodal console remote equipment. The tributary receives two audio frequency channels, a carrier derived channel and an order wire channel and returns a single audio channel. The audio component is a composite speech and digital data signal appearing on the carrier derived and return channels. The information exchanged between a tributary and the network consists of oral communications between subscribers to the system and supervisory data in the form of frequency-shift keying (FSK) signals.

The tributary equipment consists of the maintenance panel, the TTY and audio circuits, the tributary control logic, the tributary control unit, and the power distributarion. The TTY and audio circuits separate the FSK signal from the carrier channel, convert the FSK signal to de digital data, and process the audio signals. The digital data is applied to the tributary control logic and indicator lamps while the audio signal is applied to the audio circuits of the tributary control unit.

The tributary control unit serves as the operator device for the tributary equipment. It provides indicator lamps for the presentation of incoming supervisory data and pushbuttons for the subscriber to insert supervisory data for signaling the operator at the console site. The tributary control unit also includes a telephone hand-set.

The maintenance panel is used in service routines to exercise the tributary control logic. The maintenance panel incorporates switches to permit maintenance personnel to insert simulated digital data as an input to the tributary control logic. The maintenance panel also contains indicator lamps to indicate equipment malfunctions and to monitor operation of the logic circuits.



CONSOLE COMPONENTS

The console local equipment comprises two equipment areas, siconolo Operations Centra file 3 food E-Quipment Wm. The Opmanent Food of the State of t

all console local sites.

The console remote equipment is entirely contained in the Remote Equipment Van and consists of audio circuitry and switch

degree, similar and reciprocal in function to the local equipment. All van installations include air conditioning units to maintain a nominal temperature of 70° F.

Two basic types of equipment cabined arterutures have been designed for use with local and remote equipments. The type used for audio circuitry (voice, TTY modem, and switching matrix), is a shock-mounted, fixed cabinet which variously allows equipment access with ewinging panels, silding drawers, and removable plugi-in modules. The type used for logic circuitry utilizing the constitution of the control of t

The tributary equipment terminal set consists of a logic cabinet and a control unit. The equipment is packaged in a free-standing cabinet.



COMPLEMENT OF MAJOR COMPONENTS

	Logic Cabinet	Audio Circuitry Cabinet	Power Supply Cabinet	Mainte- nance Cabinet	Tape Recorder Cabinet	Oper- ator's Con- solette	Wall Display	Control Unit
Console Local Equipment- Van Operations Center	22	3	3	2	1	2	1	
Console Remote Equipment— Tributary Terminal Set—	6 (Logic, a contained	3 udio, and p in a single	2 ower circ cabinet)	2 uitry				1

CONSOLE FOLLOWENT OPERATING PROLUPEMENTS

		** **	Sp			
Power	Power	Voltage	Van Building		Temperature	
Console Local Equipment–						
Van	53.6 kw	120/208 volts, 50 or 60 cps, three phase	30 ft. van	550 sq. ft.	20°C ± 10°C	
Operations Center	15.2 kw (van) 0.6 kw (bldg.)	120 volts, 50 or 60 cps, single phase	26 ft. van	225 sq. ft.	20°C ± 10°C	
Console Remote Equipment–	27.3 kw	120/208 volts, 50 or 60 cps, three phase	26 ft. van	450 sq. ft.	20°C ± 10°C	
Tributary Terminal Set-						
Cabinet	1.5 kw	120 volts, 50 or 60 cps, single phase	-	12 sq. ft.	20°C ± 10°C	
Control Unit		_	-	Desk-top mounting	20°C ± 10°C	

LOGIC CABINETS

The logic cabinets house all electronic logic circuits needed for operation of the system. These semiconductor logic circuits are built on printed circuit plug-in cards which can be inserted and removed from the front of the eshinets. Cards are packaged 27 to a row with 2 rows to a nest and 6 nests for a logic first stock and the control of the semiconduction.

The bay is approximately 20-inches wide by 62-inches high by 7-inches deep. For shipping, the swinging bay is secured to the main structure with pawl fasteners. When the equipment reaches the site, a simple latch is used on the door to keep it closed.

Four bays are mounted to the structure which is fabricated from steel channels welded into a rigid frame. Each structure is approximately 72-inches high x 88-inches long with shock mounts at the base of the frame and between the wall of the van and the structure.

AUDIO CIRCUITRY CABINETS

The audio, TTY, and matrix switching cabinets are structurally similar. The audio cabinet for the system exists in two basic configurations, one for the console local sites and another for the remote sites. Both versions are identical in interface characteristics with the main line trunking system and both have a capacity for bridging onto five independent trunk lines. Any site can accommodate up to two branches in the five main line trunks through the use of a second bridging circuit per trunk.

The cabinet at the local site is capable of servicing two operator consoletts and up to 24 local drops. The cabinet at the remote site is capable of servicing groups of up to 24 tributaries each. Both cabinets have similar mechanical characteristics but differ in wiring and labeling. Specific variasities can be achieved by card complement and placement. The local cabinets also contain all necessary equipment to permit individual console operators access to five HF/SSB networks.



The basic function of the duplexed power supply is to convert 3-phase, 50/60 cps unpossibled, lips voltage from two separate oursets between the supplexed to the present supplexed to the supple

The duplexed power supply assembly is housed in two identical cabinets.

Each cabinet contains 15 individual regulated power supplies for 15 load channels.

MOBILE MAINTENANCE TEST CABINET

To facilitate maintenance on the indigidual cabinets while the system is in operation, a mobile test cabinet is provided that can be brought to any of the fixed cabinets. The cabinet contains a transmission test set, an oscilloscope, a square wave generator and a circuit-breaker utility-outlet panel. This unit is part of the equipment complement of both the local and remote equipment vans.

FIXED MAINTENANCE CABINET

Both the local and remote equipment vans include a fixed maintenance cabinet as part of the equipment complement. The primary function of these units is to facilitate system as well as site fault diagnosis and troubleshooting. The fixed maintenance cabinet in the local and remote equipment van contain fault summary and status indicators, message similation character generator, and TTY printenance of the property of the propert



TAPE RECORDER CABINET

Any of the four conference lines can be monitored by a tape recorder located inthe local equipment van. The control console operator has the option of switching the tape recorder to any conference line with indications of the tape recorder operation disableved at each consolette.

OPERATOR CONSOLETTE

The operator consolette is a desk-top unit utilizing a florepila housing. It provides all control syngired to perform the various percational fruitgions of which the system is capable. Since the system was first designed to be reliable and accurate and second to be used as rapidly as possible, all operator sequences that initiate or motify system operation are of the set-check-send procedure. The ability to visually check an procedure the ability to visually check the feedback needed to execution provides the feedback needed to execution and addressing



Operator Consolette

TRIBUTARY CONTROL UNIT

Similar in form to the operator consolette, the tributary control unit is also a desktop unit on which supervisory data is displayed with indicator lamps and responses. Initiated with control pushbuttons. The unit includes a telephone handset for voice communications.



Tellestern Control Unit

LOCAL DROPS

At each console local equipment location, provision has been made for up to 24 local drop telephones. These units are similar to the standard desk telephone and utilize a RECALL pushbutton and STANDBY indicator. Any local drop can request a conference or be included in any system conference.



www.usarmygermany.com

OTHER SYSTEM CONSIDERATIONS


FLEXIBLE EXPANSION

The Console System is designed in accordance with current DCA transmission interface requirements and is compatible with other DCA transmission systems.

The present configuration of the Console System can be expanded to accommodate more tributaries and local drops:

 The tributary address can range from 100 to 799, thus permitting the use of 700 tributaries.

- The number of remote units can increase from the present 10 Console Remote Equipments requirement.
- Under the present concept, the system has built into it the capability of providing for the expansion of each console remote equipment to accommodate its full complement of 24 tributaries.
- The number of local equipments in the system can also be expanded from the present complement of six.



ALTERNATE ROUTING

Alternate routing is provided on a per-line basis for that portion of the Console System circuit completing a closed-loop which exists in a portion at the console mainline network. Loop control circuits are implemented at Site 5.1 to prevent a mainline closed-loop condition. During a complete failure of one or all of the five dedicated lines within the loop portion of the main-line, contacts close automatically to provide an alternate route. Line failure detection is accomplished by line monitoring.

INTERFACE WITH OTHER SYSTEMS

Although the ET-A System is a complete communication system within itself, the mainline stations will ultimately form part of a long-haul intertheater communications network. Interface with other systems in compliance with DCA standards can be made at the voice channel level on a 4-wire basis or at the channel group level. The multiplex equipment does not include accommodations for in-band signaling, This must be provided by the terminating equipment. The ET-A Console System includes in-band teletype channels for supervisory signals. An out-of-band signaling facility is included with each channel in the multiplex equipment. Therefore, a signaling interface using E and M techniques is provided for interconnection with other systems on a 4-wire basis.

AUTOVON

The capability of interworking with the

DCA's automatic voice network, AUTO-VON, is being introduced to the Console System to have:

- Primarily, an increased systems survivability through the alternate routing on a per-channel basis of the Console System's five dedicated channels
- Secondarily, the tributary access to and from the AUTOVON subscribers for administrative traffic is pre-emptable for command and control traffic

Each mainline console site will have access to AUTOVON via five dedicated tie lines All console local sites may access and be accessed by AUTOVON to maintain Console System continuity while all console remote sites can only be accessed by AUTO-VON for this service. A request by a console local site for a trunk is accommodated on a preprogrammed priority basis at the AUTOVON switch, A maximum of five trunks can be requested for use between sites. This use of common-user-switched trunks allows these trunks to be used for other services when they are not being used by the Console System, Automatic pre-emption of busy trunks for command and control console system traffic is accomplished by the AUTOVON switch whenever a console local operator requests a trunk.

Administrative traffic tie lines to AUTO-VON are terminated only at each of the console remote sites.

The connections to AUTOVON add to the survivability of the Console System and provide channels for administrative traffic to and from tributaries without impairing the operation of the Console System.



TRAINING FACILITY

A Console System training facility to be centrally located in Europe has the primary purpose of instructing technicians in the maintenance, repair and operation of the Console System equipment. An additional mission is to train local and tributary operators in the Console System operational procedure.

Although the traffic handling capability is somewhat restricted to the use of the tributaries and three local drops, there is no extriction on the demonstration capabilities of various system functions relating to the normally busy system. The Training Facility consists of:

 A console local site including the Operations Center equipment and its associated console local equipment and three local drop sets serviced by the

A console remote site to perform the necessary remote switching.
 A standby console site to provide dem-


- A standby console site to provide demonstration of command and control switching.
- Three tributary terminal sets to implement two sectors of simultaneous operation.

Maintenance personnel are trained in service procedures, and trouble-shooting techniques. They obtain a firm understanding of the philosophy and limitations of on-site maintenance.

Operators learn system control functions, over-all system operation, programming and use of the diode patch fields, and the philosophy and use of the cable patch fields in the console local and remote equipments.

EUROPEAN COMMAND and CONTROL CONSOLE SYSTEM EUROPEAN TROPOSPHERIC SCATTER COMMUNICATIONS SYSTEM-ARMY PORTION developed for the U.S. ARMY STRATEGIC COMMUNICATIONS COMMAND CONTRACT NO. DA36-039-SC88783

by ITT FEDERAL LABORATORIES



Printed in U.S.A.

Prepared by ITTFL Technical Publications

www.usarmygermany.com